

EXTERIOR LIGHTING

Measure Description	Fixture Type	Lighting (Pre)	Lighting (Post)	Model #	Make	Cost
Replace Select Exterior Lighting with LED Fixtures	Knuckle Flood	HID 50W	LED 15-Watt Knuckle Flood	X34-16L	RAB	
	Wallpack	HID 400W	LED 80-Watt Wallpack w/ Photocell	WP-OP80U-50B	Maxlite	
	Wallpack	HID 70W-100W	LED 28-Watt Wallpack w/ Photocell	WP-OP28U-50B-PC	Maxlite	
	Jelly Jar/Cage	LED 6W 1L	Jelly Jar Fixture w/ LED 4.5-Watt Lamp	VC150I M12, w/ LED4.5A19/DIM/O/850/RP	Lithonia	
	Vandal	HPS 35W	LED 6-Watt Small Vandal	VAN1LED6NW	RAB	
	Mini Wallpack / Porch Light	CFL 26W-42W / HPS 70W	LED 15-Watt Wallpack w/ Photocell	SEC15U50BPC	Maxlite	
	Knuckle Flood	Halogen 500W	LED 66-Watt Knuckle Flood	QTE-LED-P3-40K-120-THK-DDB-M6	Lithonia	
	10'-20' Pole Yoke Flood	HPS 250W	LED 66-Watt Pole Yoke Flood	QTE LED P3 40K 120 YK DDBM6	Lithonia	
	Yoke Flood	MH 250W	LED 66-Watt Yoke Flood	QTE LED P3 40K 120 YK DDBM6	Lithonia	
	Security Flood 2-Head	CFL 13W 2L	LED 25-Watt Security 2-Head	OLF-3RH-40K-120-PE-DDB-M4	Lithonia	
	Security Flood 3-Head	CFL 13W 3L	LED 36-Watt Security 3-Head	OLF-3RH-40K-120-PE-DDB-M4	Lithonia	
	Yoke Flood	MH 400W	LED 120-Watt Flood	FML120UW-40B	Maxlite	
	Porch Light / Jelly Jar / Vandal	CFL 13W-26W / HPS 35W	LED 10-Watt Wallpack w/ Photocell	E2WPC10L-750	Energetic	
	15'-25' Pole Barn Light	HID 150W	LED 30-Watt Barn w/ Photocell	E1ALB30-750 E	Energetic	
	SM Canopy 1'x1' / SM Round	HID 70W-150W	LED 20-Watt Canopy	CPL20BUC50B	Maxlite	
	20'-25' Pole Top Box	HID 400W	LED 78-Watt Pole Top	ALED5T78N	RAB	
	10'-15' Pole Top Box	HID 150W	LED 26-Watt Pole Top	ALED5T26N	RAB	
	25'-35' Pole Shoebox	HID 400W	LED 147-Watt Pole Shoebox w/ Photocell	AL-150W	ILP	
	*15'-25' Pole Welded Slip-Fit Knuckle Flood	HID 250W	LED 94-Watt Pole Shoebox w/ PC & 25' Steel Pole	AL-90W	ILP	
	10'-20' Pole Shoebox	HID 150W	LED 58-Watt Pole Shoebox w/ Photocell	AL-56W	ILP	
Wall Mount Direct	HID 100W	LED 58-Watt Wall Shoebox w/ Photocell	AL-56W	ILP		
* Only one example of this exists. The slip fit mount is welded to the pole, and district electrician noted that they do not know how to secure electricity to this pole.						
Measure Description	Fixture Type	Lighting (Pre)	Lighting (Post)	Model #	Make	Cost
Replace Select Exterior Lighting with LED Lamps	Various	HPS 70W	LED 23-Watt Retro Lamp Ballast Bypass	A23-24-EX39-840-ND	RAB	
	SM 4' VP	F32T8	LED 14-Watt 4' Tubes & Driver	13T8/MAS/48-840, Advance Driver	Signify/Philips	
	WM Door Light	F17T82L	LED 8-Watt 2' Tubes & Driver	7T8/MAS/24-840, Advance Driver	Signify/Philips	
	Various	CFQ 18W	LED 9-Watt 4-pin Lamp Ballast Bypass	PLC-9-H-840-BYP	RAB	
	Recessed 1'x1'	CFQ 26W	LED 8.5-Watt 4-pin Lamp & Driver	8.5PL-C/T LED/26H-4000	Signify/Philips	
	10'-15' Pole-Top Decorative	MH 150W	LED 36-Watt Retro Lamp Ballast Bypass	HID-36-E26-850-BYP-PT	RAB	
	20'-25' Pole-Top Decorative	MH 250W	LED 63-Watt Retro Lamp Ballast Bypass	HID-63-EX39-840-BYP-PT	RAB	
	20'-25' Pole-Top Decorative (2-Head)	MH 250W	LED 63-Watt Retro Lamp Ballast Bypass	HID-63-EX39-840-BYP-PT	RAB	